MDVR SETTING (4G)

(1) Please put in 3G/4G Sim Card.



(2) Enter MENU → select SYSTEM → PERIPHERAL → NETWORK



(3) Press > on remote control to select " MOBILE NETWORK "



(4) Set "ACCOUNT" & "PASSWORD"



* Reminder * : Account & Password must synchronize with AP: user account.

Server							
File	Windows	Control	Setti	ngs	Help		
<u> </u>	. 🛃	🧀 Ø		Serve	r/Client		
		<u> </u>		User A	Account		
				Video	-upload	config	
				Push (Control		
				Other			

(5)Please select **MOBILE NETWORK** \rightarrow set the detail parameters depend on your country.

2016/03/11 1	14:20:47 SD1	0% GI	I-0123456	2016/03/11 14:2	21:08 SD1 0%	GII-0123456
GROUP ACCOUNT PASSWORD SERVER ADDRESS ETHERNET WIFI	NETWORK	SET SET SET SET SET		N MOBILE NETWORK APN DIAL NUMBER USER	IETWORK LE NETWORK ON INTERNET *99#	
MOBILE NETWORK		SET		PASSWORD PIN	0000	

(6)Please select SEVER ADDRESS→ choose type to **STATIC IP** and input the server IP address.

	2016/03/11 1	4:22:59	SD1	0%	GII-012345	5	2016/03/1	1 14:25:57	SD1	1%	GII-C	012345
48.		NETWORK				66		NETWORK				
and a	GROUP ACCOUNT			S	SET			SERVER ADD	RESS			
	PASSWORD			5	SET	100	TYPE			STATIC	IP	H
	SERVER ADDRESS			5	ET		SERVER IP		22	0.130.	6. 5	50
he a	ETHERNET			5	SET							
1	WIFI			8	SET	5						
	MOBILE NEIWORK			5	561							
						4						
						6						

(7)Back to SYSTEM SETTING \rightarrow set "CAR ID" .

	2016/03/11	16:44:05	0%	JIG2808
	SY	STEM SETTINGS		
r	LANGUAGE FORMAT PASSWORD DATE AND TIME		ENGLIS SET SET SET	5H D
	CAR ID SYSTEM AUDIO C BOOT DELAY TIM	ONFIG E	SET SET 3 SEC	
r	PERIPHERAL DEFAULT		SET SET	



(8)Reboot the MDVR.



(9) Setting Completed \rightarrow You will see the sign "G", "CAR ID" and "IP adress" on screen.

