Firmware Upgrade

- 1. MDVR upgrade firmware there must need the following one:
 - (1) V1.3.8GT_2016-06-03.upg
 - (2) V1.3.8X_2016-06-03.upg
- 2. Copy and paste firmware files to the root directory of a removable USB drive.
- 3. Take the removable USB drive which has the three files and connect to the USB port of the MDVR.

Confirm the USB drive connection which is ready for update by checking the monitor display for the USB icon that will change to green.

	2015/08/26 15:2	26:13 R46%	ABC-2808						
	System Information								
	version** VER. 1.0.8G VIDEO SYSTEM	2015/07/28 ** T PAL	390						
	HD TOSHIBA MK5059GS								
	SD SD NOT EXIST								
	MAC	00:1B:CC:00:66	5:37						
	Ethernet IP	192.168.1.206							
	Wifi IP	192.168.1.149							
	Mobile Network	No IP							
0	.0 mile/h 39°C 11.9V	HDD SD	USB R A						

3. IR remote control, press the down button (\downarrow)

The monitor display will show an information dialog box inquiring whether you want to upgrade the Firmware.



Firmware version and system Query :

On Real-time monitor mode, press up button O of Remote controller to call System info page. The System information page would shows the Firmware version \cdot The capacity of a hard disk drive \cdot Ethernet MAC and information.

		2015/08/	21 12:2	5:32		JET-2808G		
System Information								
¥	version VIDEO S	n** VER. SYSTEM	1.0.8G	2015/07/28 PAL	** T	267		
4	HD	TOSHIBA 500 GB	MK50590	S				
	SD	STORAGE 3 GB	DEVICE					
	MAC			00:1B:CC	:00:66	:37		
	Etherne	et IP		192.168.1	L.206	DAMAGE ST		
	Wifi I	P		192.168.1	L.149			
	Mobile	Network		10.224.13	38.38			
		1	E					